



High Accuracy Current and Power Monitor with I²C Compatible Interface

Description

The CAD2726 is a current shunt and power monitor with an I^2C interface.


The CAD2726 monitors both shunt voltage drop and bus supply voltage. The device can directly read current in amperes and power in watts, with programmable calibration value, conversion times, and averaging options, combined with an internal multiplier. It supports up to 16 programmable addresses on I²C interface.

Features


- Operating Voltage: 2.7V to 5.5V
- Bus Voltage (Input Voltage): 0V to 36 V
- 16-Bit Delta-Sigma ADC
- Reports Current, Voltage, and Power
- Programmable Calibration Value, Conversion times, and Averaging Options
- High Accuracy:
 - 0.1 % Gain Error (Max.)
 - 10 µV Offset (Max.)
- Compatible with SMBus and I²C interface
- I²C Speed up to 2.94MHz (High-Speed Mode)
- Noise Filter on SCL/SDA inputs
- 16 Programmable Addresses
- Operating temperature Range: -40°C to 125°C
- Available Package: DFN3x3-10, MSOP-10

Application

- Server
- Telecom equipment
- Notebook Computers
- Power Management
- Battery Chargers
- Power Supplies
- Test Equipment



DFN3X3-10(Package code DN)




MSOP-10(Package Code MM)

PIN Configurations (Top View)



High Accuracy Current and Power Monitor with I²C Compatible Interface

Typical Application



Pin Description


| PIN Name | PIN No. | Туре | Description | | |
|----------|---------|----------------|--|--|--|
| A1 | 1 | Digital Input | Address pin. Connect to GND, SCL, SDA, or VCC. | | |
| A0 | 2 | Digital Input | Address pin. Connect to GND, SCL, SDA, or VCC. | | |
| Alert | 3 | Digital Output | Multi-functional alert, open-drain output. Can be floated. | | |
| SDA | 4 | Digital I/O | Serial bus data line, open-drain output & input. | | |
| SCL | 5 | Digital Input | Serial bus clock line. | | |
| VCC | 6 | Power | Power supply, 2.7V to 5.5 V. | | |
| GND | 7 | Ground | Ground. | | |
| VBUS | 8 | Analog Input | Bus voltage input. | | |
| IN- | 9 | Analog Input | Connect to load side if shunt resistor. | | |
| IN+ | 10 | Analog Input | Connect to supply side of shunt resistor. | | |



CAD2726


High Accuracy Current and Power Monitor with I²C Compatible Interface

Function Block



Function Block Diagram

Ordering Information



| Order PN | Green | Package | Marking ID | Packing | MPQ | Operation Temperature |
|------------|--------------|-----------|----------------|-------------|-------|--------------------------|
| CAD2726DNR | Halogen free | DFN3x3-10 | 2726 YWWAXX | Tape & Reel | 3,000 | -40℃~+125℃ |
| CAD2726MMR | Halogen free | MSOP-10 | 2726 YWWAXX | Tape & Reel | 3,000 | -40℃~+125℃ |



High Accuracy Current and Power Monitor with I²C Compatible Interface



SENSYLINK Microelectronics Inc.

www.sensylink.com

IMPORTANT NOTICE

SENSYLINK Microelectronics Inc. reserves the right to make modifications, enhancements, improvements, corrections or other changes without further notice to this document and any product described herein or to discontinue any product or service. Customers should obtain the latest relevant information before placing orders and should verify the latest and complete information. SENSYLINK Microelectronics does not assume any responsibility for use of any product, nor does SENSYLINK Microelectronics any liability arising out of the application or use of this document or any product or circuit described herein. SENSYLINK Microelectronics assumes no liability for applications assistance or the design of Customers' products. Customers are responsible for their products and applications using SENSYLINK Microelectronics components. SENSYLINK Microelectronics does not convey any license under its patent or trademark rights nor the other rights.

SENSYLINK Microelectronics Inc. © 2015 - 2023.